

Single Phase Energy Hub Inverter with Prism Technology

For North America

SE3000H-US / SE3800H-US / SE6000H-US / SE7600H-US /
SE10000H-US / SE11400H-US⁽¹⁾



Optimized battery storage with HD-Wave technology

- Record-breaking 99% weighted efficiency with 200% DC oversizing
- Small, lightweight, and easy to install
- Modular design, future ready with optional upgrades to:
 - DC-coupled storage for full or partial home backup
 - Built-in consumption monitoring
 - Direct connection to the SolarEdge smart EV charger
- Multi-inverter, scalable storage solution
 - With enhanced battery power up to 10kW
- Integrated arc fault protection and rapid shutdown for NEC 2014, NEC 2017 and NEC 2020, per article 690.11 and 690.12
- Embedded revenue grade production data, ANSI C12.20 Class 0.5

/ Single Phase Energy Hub Inverter with Prism Technology For North America

SE3000H-US / SE3800H-US / SE6000H-US / SE7600H-US / SE10000H-US / SE11400H-US⁽¹⁾

SE3000H-US SE3800H-US SE6000H-US SE7600H-US SE10000H-US SE11400H-US UNITS

OUTPUT - AC ON GRID

Rated AC Power	3000	3800 @ 240V 3300 @ 208V	6000 @ 240V 5000 @ 208V	7600	10000	11400 @ 240V 10000 @ 208V	W
Maximum AC Power Output	3000	3800 @ 240V 3300 @ 208V	6000 @ 240V 5000 @ 208V	7600	10000	11400 @ 240V 10000 @ 208V	W
AC Frequency Range (min - nom - max)	59.3 - 60 - 60.5 ⁽²⁾						Hz
Maximum Continuous Output Current @ 240V	12.5	16	25	32	42	47.5	A
Maximum Continuous Output Current @ 208V	-	16	24	-	-	48.5	A
GFDI Threshold	1						A
Total Harmonic Distortion (THD)	<3						%
Power Factor	1, adjustable -0.85 to 0.85						
Utility Monitoring, Islanding Protection, Country Configurable Thresholds	Yes						
Charge Battery from AC (if allowed)	Yes						
Typical Nighttime Power Consumption	<2.5						W

OUTPUT - AC BACKUP⁽³⁾

Rated AC Power in Backup Operation ⁽⁴⁾	3000	3800 7600*	6000	7600 10300*	10000	10300	W
AC L-L Output Voltage Range in Backup	211 - 264						Vac
AC L-N Output Voltage Range in Backup	105 - 132						Vac
AC Frequency Range in Backup (min - nom - max)	55 - 60 - 65						Hz
Maximum Continuous Output Current in Backup Operation	12.5	16 32*	25	32 43*	42	43	A
GFDI	1						A
THD	<5						%

OUTPUT - SMART EV CHARGER AC

Rated AC Power	9600						W
AC Output Voltage Range	211 - 264						Vac
On-Grid AC Frequency Range (min - nom - max)	59.3 - 60 - 60.5						Hz
Maximum Continuous Output Current @240V (grid, PV and battery)	40						Aac

INPUT - DC (PV AND BATTERY)

Transformer-less, Ungrounded	Yes						
Max Input Voltage	480						Vdc
Nom DC Input Voltage	380						Vdc
Reverse-Polarity Protection	Yes						
Ground-Fault Isolation Detection	600k Ω Sensitivity						

INPUT - DC (PV)

Maximum DC Power @ 240V	6000	7600	12000	15200	22000	22800	W
		15200*		22800*			
Maximum DC Power @ 208V	-	6600	10000	-	-	20000	W
Maximum Input Current ⁽⁵⁾ @ 240V	8.5	10.5	16.5	20	27	31	Adc
		20*		31*			
Maximum Input Current ⁽⁵⁾ @ 208V	-	9	13.5	-	-	27	Adc
Max. Input Short Circuit Current	45						Adc
Maximum Inverter Efficiency	99	99.2					%
CEC Weighted Efficiency	99					99 @ 240V 98.5 @ 208V	%
2-pole Disconnection	Yes						

* Supported with PN SExxxxH-USMMxxxxxx or SExxxxH-USMNxxxxxx

(1) These specifications apply to inverters with part numbers SExxxxH-USMMxxxxxx or SExxxxH-USMNxxxxxx and connection unit model number DCD-1PH-US-PxH-F-x

(2) For other regional settings please contact SolarEdge support

(3) Not designed for standalone applications and requires AC for commissioning. Backup functionality is only supported for 240V grid

(4) Rated AC power in Backup Operation are valid for installations with multiple inverters. For a single backup inverter operation, rated AC power in Backup is 90% of the value stated

(5) A higher current source may be used; the inverter will limit its input current to the values stated

/ Single Phase Energy Hub Inverter with Prism Technology For North America

SE3000H-US / SE3800H-US / SE6000H-US / SE7600H-US / SE10000H-US / SE11400H-US⁽¹⁾

SE3000H-US								SE3800H-US	SE6000H-US	SE7600H-US	SE10000H-US	SE11400H-US	UNITS
INPUT - DC (BATTERY)													
Supported Battery Types				SolarEdge Energy Bank, LG RESU Prime ⁽⁶⁾									
Number of Batteries per Inverter				Up to 3 SolarEdge Energy Bank, up to 2 LG RESU Prime									
Continuous Power ⁽⁷⁾				6000	7600	10000					W		
Peak Power ⁽⁷⁾				6000	7600	10000					W		
Max Input Current				16	20	26.5					Adc		
2-pole Disconnection				Yes									
SMART ENERGY CAPABILITIES													
Consumption Metering				Built - in ⁽⁸⁾									
Backup & Battery Storage				With Backup Interface (purchased separately) for service up to 200A; Up to 3 inverters									
EV Charging				Direct connection to Smart EV charger									
ADDITIONAL FEATURES													
Supported Communication Interfaces				RS485, Ethernet, Cellular ⁽⁹⁾ , Wi-Fi (optional), SolarEdge Energy Net (optional)									
Revenue Grade Metering, ANSI C12.20				Built - in ⁽⁸⁾									
Integrated AC, DC and Communication Connection Unit				Yes									
Inverter Commissioning				With the SetApp mobile application using built-in Wi-Fi Access Point for local connection									
DC Voltage Rapid Shutdown (PV and Battery)				Yes, according to NEC 2014, NEC 2017 and NEC 2020 690.12									
STANDARD COMPLIANCE													
Safety				UL1741, UL1741 SA, UL1741 PCS, UL1699B, UL1998, UL9540, CSA 22.2									
Grid Connection Standards				IEEE1547, Rule 21, Rule 14H									
Emissions				FCC part 15 class B									
INSTALLATION SPECIFICATIONS													
AC Output and EV AC Output Conduit Size / AWG Range				1" maximum / 14-4 AWG									
DC Input (PV and Battery) Conduit Size / AWG Range				1" maximum / 14-6 AWG									
Dimensions with Connection Unit (H x W x D)				17.7 x 14.6 x 6.8 / 450 x 370 x 174			17.7 x 14.6 x 6.8 / 450 x 370 x 174	17.7 x 14.6 x 6.8 / 450 x 370 x 174			in / mm		
							17.7 x 14.6 x 6.8 / 450 x 370 x 174*						
Weight with Connection Unit				26 / 11.8			26 / 11.8	41.7 / 18.9			lb / kg		
							41.7/ 18.9*						
Noise				< 25	< 25 < 50*	< 25	< 50				dBA		
Cooling				Natural Convection									
Operating Temperature Range				-40 to +140 / -40 to +60 ⁽¹⁰⁾								°F / °C	
Protection Rating				NEMA 4									

(6) The part numbers SExxxH-USxMxxxx only support the SolarEdge Energy Bank. The part numbers SExxxH-USxNxxxx support both SolarEdge Energy Bank and LG RESU Prime batteries
Requires supporting inverter firmware

(7) Discharge power is limited up to the inverter rated AC power for on-grid and backup applications

(8) For consumption metering current transformers should be ordered separately: SECT-SPL-225A-T-20 or SEACT0750-400NA-20 units per box. Revenue grade metering is only for production metering

(9) Information concerning the Data Plan's terms & conditions is available in the following link:

<https://www.solaredge.com/sites/default/files/se-communication-plan-terms-and-conditions-eng.pdf>

(10) Full power up to at least 50°C / 122°F; for power de-rating information refer to: <https://www.solaredge.com/sites/default/files/se-temperature-derating-note-na.pdf>