

Automatic Standby Gaseous Generator

SPECIFICATIONS (LP/NG)	48kW	60kW	80kW
Model Number	RG04845	RG06045	RG08045
Output Amperage LP/NG 120/240 V, 1 ϕ 1.0 pf	200/200	250/250	Contact Factory / 333
Output Amperage LP/NG 120/208 V, 3 ϕ 0.8 pf	167/167	208/208	Contact Factory / 277
Output Amperage LP/NG 120/240 V, 3 ϕ 0.8 pf	144/144	180/180	Contact Factory / 240
Output Amperage LP/NG 277/480 V, 3 ϕ 0.8 pf	72/72	90/90	Contact Factory / 120
Engine/Alternator RPM	1800		
Engine	4.5L, in-line 4-cyl.	4.5L Turbo, in-line 4-cyl.	4.5L Turbo, in-line 4-cyl.
Fuel Consumption @ full load - LPG cu. ft/hr (gal/hr)	240.4 (6.61)	305.6 (8.4)	393.2 (10.8)
Fuel Consumption @ full load - NG cu. ft/hr	604	808	1063
Quiet-Test Mode	Yes		
db(A) at Exercise	68		
db(A) Normal Operating Load	70	72	74
Dimensions (L" x W" x H")	83 x 35 x 46	97 x 38 x 49	97 x 38 x 49
Generator Weight (lbs.)	1781	1912	2022
Mobile Link Connectivity Standard via Wi-Fi Ethernet Module	Yes		
SCAQMD Model	•	•	•



NATIONWIDE DEALER SERVICE NETWORK

Generac's commitment to service includes scheduled maintenance programs, warranty assistance and emergency service to ensure that Generac customers are never left powerless. The largest nationwide dealer network has factory-trained technicians on staff and maintains large inventories of Generac parts, components and accessories. Find a dealer near you at Generac.com.

Generac Power Systems, Inc.
S45 W29290 Hwy. 59, Waukesha, WI 53189

www.Generac.com | 888-GENERAC (436-3722)

201902154 REV 06/20

©2020 Generac Power Systems. All rights reserved.
Specifications are subject to change without notice.

GENERAC®